

# HPE Networking Legacy Product Family Mini-GBIC and SFP Support Matrix

			Genuine HPE Mini-GBICs and SFPs				
			Gigabit "B" and "C" versions				
HPE Networking Switch Series	Product Name	Product Number	Gigabit-SX, LX, LH (J4858B, J4859B, J4860B) (J4858C, J4859C, J4860C)		1000BASE-T <sup>1</sup> (J8177B) (J8177C)		Gigabit-BX (J9142B, J9143B)
			Supported with This Software	Supported with This Software	Supported with This Software	Supported with This Software	Supported with This Software
1400	Switch 1400 24G	J9078A	all software versions	all software versions	(not supported)	(not supported)	all software versions
1410	1410 24G Switch	J9561A	all software versions	all software versions	(not supported)	(not supported)	all software versions
1700	Switch 1700 24	J9080A	all software versions	VB.01.09 and later	(not supported)	(not supported)	VB.02.00 and later
1800	Switch 1800 24G	J9028A/B	all software versions	PB.02.09 and later	(not supported)	(not supported)	PB.03.00 and later
1810	1810 24G Switch	J9450A	all software versions (Gig-LH in J9450A only)	all software versions (Gig-LH in J9450A only)	(not supported)	(not supported)	(not supported)
	1810 48G Switch	J9660A			all software versions	all software versions	
	1810 24 v2 Switch 1810 24G v2 Switch PS 1810 24G Switch	J9801A J9803A J9834A	all software versions (Gig-LH not supported)	all software versions (Gig-LH not supported)	all software versions	all software versions	(not supported)
1820	1820 24G Switch	J9980A	(not supported)	all software versions (J4860C not supported)	(not supported)	all software versions	(not supported)
	1820 48G Switch	J9981A					
	1820 24G PoE+ (185W) Switch	J9983A					
	1820 48G PoE+ (370W) Switch	J9984A					
2510	Switch 2510 24	J9019A/B	all software versions	all software versions	(not supported)	(not supported)	Q.11.16 and later
	Switch 2510 48	J9020A			all software versions	all software versions	U.11.10 and later
	Switch 2510G 24	J9279A	all software versions	all software versions	(not supported)	(not supported)	Y.11.03 and later
	Switch 2510G 48	J9280A					
2520	2520 8 PoE Switch	J9137A	all software versions	all software versions	(not supported)	(not supported)	all software versions
	2520 24 PoE Switch	J9138A					
	2520G 8 PoE Switch	J9298A					
	2520G 24 PoE Switch	J9299A					

**Genuine HPE Mini-GBICs and SFPs (continued)**

**Gigabit "B" and "C" versions**

HPE Networking Switch Series	Product Name	Product Number	Gigabit-SX, LX, LH (J4858B, J4859B, J4860B)   (J4858C, J4859C, J4860C)		1000BASE-T <sup>1</sup> (J8177B)   (J8177C)		Gigabit-BX (J9142B, J9143B)
			Supported with This Software	Supported with This Software	Supported with This Software	Supported with This Software	Supported with This Software
2530	2530 8 Switch	J9783A	all software versions	all software versions	(not supported)	(not supported)	all software versions
	2530 24 Switch	J9782A	all software versions	all software versions	all software versions	all software versions	
	2530 48 Switch	J9781A			(not supported)	(not supported)	
	2530 8G Switch	J9777A	all software versions	all software versions	all software versions	all software versions	
	2530 24G Switch	J9776A			(not supported)	(not supported)	
	2530 48G Switch	J9775A	all software versions	all software versions	all software versions	all software versions	
	2530 8 PoE+ Switch	J9780A			(not supported)	(not supported)	
	2530 24 PoE+ Switch	J9779A	all software versions	all software versions	all software versions	all software versions	
	2530 48 PoE+ Switch	J9778A			(not supported)	(not supported)	
	2530 8G PoE+ Switch	J9774A	all software versions	all software versions	all software versions	all software versions	
	2530 24G PoE+ Switch	J9773A			all software versions	all software versions	
	2530 48G PoE+ Switch	J9772A					
	2530 24G 2SFP+ Switch	J9856A					
	2530 48G 2SFP+ Switch	J9855A					
2530 24G PoE+ 2SFP+ Switch	J9854A						
2530 48G PoE+ 2SFP+ Switch	J9853A						
2600	Switch 2626	J4899A/B/C	all software versions	H.08.98 and later	(not supported)	(not supported)	H.10.72 and later
	Switch 2650	J4900A/B/C					
	Switch 2626 PWR	J8164A					
	Switch 2650 PWR	J8165A					
	Switch 2600 8 PWR	J8762A					
2610	Switch 2610 24	J9085A	all software versions	all software versions	all software versions	all software versions	R.11.22 and later
	Switch 2610 48	J9088A					
	Switch 2610 24 PWR	J9087A					
	Switch 2610 48 PWR	J9089A					
	Switch 2610 24/12PWR	J9086A					
2615	2615 8 PoE Switch	J9565A	all software versions	all software versions	(not supported)	(not supported)	all software versions
2620	2620 24 Switch	J9623A	all software versions	all software versions	all software versions	all software versions	all software versions
	2620 48 Switch	J9626A					
	2620 24 PoE+ Switch	J9625A					
	2620 48 PoE+ Switch	J9627A					
	2620 24 PPoE+ Switch	J9624A					
2800	Switch 2824	J4903A	all software versions	i.08.103 and later	(not supported)	(not supported)	i.10.69 and later
	Switch 2848	J4904A					

**Genuine HPE Mini-GBICs and SFPs (continued)**

**Gigabit "B" and "C" versions**

HPE Networking Switch Series	Product Name	Product Number	Gigabit-SX, LX, LH (J4858B, J4859B, J4860B)   (J4858C, J4859C, J4860C)		1000BASE-T <sup>1</sup> (J8177B)   (J8177C)		Gigabit-BX (J9142B, J9143B)
			Supported with This Software	Supported with This Software	Supported with This Software	Supported with This Software	Supported with This Software
2810	Switch 2810 24G Switch 2810 48G	J9021A J9022A	all software versions	all software versions	(not supported)	(not supported)	N.11.14 and later
2900	Switch 2900 24G Switch 2900 48G	J9049A J9050A	all software versions	all software versions	(not supported)	(not supported)	T.13.45 and later
2910al	2910al 24G Switch 2910al 48G Switch 2910al 24G PoE+ Switch 2910al 48G PoE+ Switch	J9145A J9147A J9146A J9148A	all software versions	all software versions	(not supported)	(not supported)	all software versions
2915	2915 8G PoE Switch	J9562A	all software versions	all software versions	(not supported)	(not supported)	all software versions
2920	2920 24G Switch 2920 48G Switch 2920 24G PoE+ Switch 2920 48G PoE+ Switch 2920 48G POE+ 740W Switch 2-Port 10GbE SFP+ Module	J9726A J9728A J9727A J9729A J9836A J9731A	all software versions	all software versions	(not supported)	(not supported)	all software versions
Aruba 2930F	2930F 24G 4SFP+ Switch 2930F 48G 4SFP+ Switch 2930F 24G PoE+ 4SFP+ Switch 2930F 48G PoE+ 4SFP+ Switch 2930F 8G PoE+ 2SFP+ Switch 2930F 24G PoE+ 4SFP+ TAA Switch 2930F 48G PoE+ 4SFP+ TAA Switch 2930F 24G 4SFP Switch 2930F 48G 4SFP Switch 2930F 24G PoE+ 4SFP Switch 2930F 48G PoE+ 4SFP Switch	JL253A JL254A JL255A JL256A JL258A JL263A JL264A JL259A JL260A JL261A JL262A	(not supported)	all software versions	(not supported)	all software versions	all software versions
3400cl	Switch 3400cl 24G Switch 3400cl 48G	J4905A J4906A	all software versions	all software versions	(not supported)	(not supported)	(not supported)

Genuine HPE Mini-GBICs and SFPs (continued)

Gigabit "B" and "C" versions

HPE Networking Switch Series	Product Name	Product Number	Gigabit-SX, LX, LH (J4858B, J4859B, J4860B) (J4858C, J4859C, J4860C)		1000BASE-T <sup>1</sup> (J8177B) (J8177C)		Gigabit-BX (J9142B, J9143B)
			Supported with This Software	Supported with This Software	Supported with This Software	Supported with This Software	Supported with This Software
3500	3500 24 Switch 3500 48 Switch 3500 24 PoE Switch 3500 48 PoE Switch	J9470A J9472A J9471A J9473A	K.14.31 and later	K.14.31 and later	(not supported)	(not supported)	K.14.31 and later
3500yl	Switch 3500yl 24G PWR Switch 3500yl 48G PWR	J8692A J8693A	all software versions	all software versions	(not supported)	(not supported)	K.13.45 and later
	3500yl 24G PoE+ Switch 3500yl 48G PoE+ Switch	J9310A J9311A	K.14.50 and later	K.14.50 and later			K.14.50 and later
3800	3800 24G 2SFP+ Switch 3800 48G 4SFP+ Switch 3800 24G PoE+ 2SFP+ Switch 3800 48G PoE+ 4SFP+ Switch 3800 24SFP 2SFP+ Switch	J9575A J9576A J9573A J9574A J9584A	all software versions	all software versions	all software versions	all software versions	all software versions
Aruba 3810M	3810M 24G 1-slot Switch 3810M 48G 1-slot Switch 3810M 24G PoE+ 1-slot Switch 3810M 48G PoE+ 1-slot Switch 3810M 16SFP+ 2-slot Switch 3810M 40G 8 HPE Smart Rate PoE+ 1-slot Switch  *For use in the <b>JL075A</b> 3810M switch or in any 3810M switch with a <b>JL083A</b> Aruba 3810M 4SFP+ Module installed.	JL071A* JL072A* JL073A* JL074A* JL075A JL076A*	all software versions	all software versions	all software versions	all software versions	all software versions
4100gl	Switch gl 6-Port Mini-GBIC Module Switch gl 20-Port 10/100/1000 Module	J4893A J4908A	all software versions	G.07.103 and later	G.07.69 and later	G.07.69 and later	(not supported)
4200vl	Switch vl 4-Port Mini-GBIC Module	J8776A	all software versions	all software versions	all software versions	all software versions	L.11.16 and later
	Switch vl 20-Port Gig-T + 4-Port SFP Module	J9033A					
5300xl	Switch xl 4-Port Mini-GBIC Module	J4878A/B	all software versions	E.10.36 and later	E.09.22 and later	E.09.22 and later	E.11.08 and later
	Switch xl 16-Port 10/100/1000 Module	J4907A			(not supported)	(not supported)	

**Genuine HPE Mini-GBICs and SFPs (continued)**

**Gigabit "B" and "C" versions**

HPE Networking Switch Series	Product Name	Product Number	Gigabit-SX, LX, LH (J4858B, J4859B, J4860B) (J4858C, J4859C, J4860C)		1000BASE-T <sup>1</sup> (J8177B) (J8177C)		Gigabit-BX (J9142B, J9143B)
			Supported with This Software	Supported with This Software	Supported with This Software	Supported with This Software	Supported with This Software
5400zl	Switch zl 20-Port 10/100/1000 + 4-Port Mini-GBIC Module	J8705A	all software versions	all software versions	all software versions	all software versions	K.13.45 and later
	Switch zl 24-Port Mini-GBIC Module	J8706A	all software versions	all software versions	all software versions	all software versions	K.13.45 and later
	20-Port 10/100/1000 PoE+ and 4-Port SFP zl Module	J9308A	K.14.34 and later	K.14.34 and later	K.14.34 and later	K.14.34 and later	K.14.34 and later
	24-Port SFP v2 zl Module	J9537A	K.15.02.0004 and later	K.15.02.0004 and later	K.15.02.0004 and later	K.15.02.0004 and later	K.15.02.0004 and later
	20-Port Gig-T / 4-Port SFP v2 zl Module	J9549A					
	20-Port Gig-T PoE+ / 4-Port SFP v2 zl Module	J9535A					
12-Port Gig-T PoE+ / 12-Port SFP v2 zl Module	J9637A						
8-Port 10 GbE SFP+ v2 zl Module	J9538A	(not supported)			(not supported)		
20-Port Gig-T / 2-Port SFP+ v2 zl Module	J9548A						
20-Port Gig-T PoE+ / 2-Port SFP+ v2 zl Module	J9536A						
5400R	24-Port SFP v2 zl Module	J9537A	all software versions	all software versions	all software versions	all software versions	all software versions
	20-Port Gig-T / 4-Port SFP v2 zl Module	J9549A					
	20-Port Gig-T PoE+ / 4-Port SFP v2 zl Module	J9535A					
	12-Port Gig-T PoE+ / 12-Port SFP v2 zl Module	J9637A					
	8-Port 10 GbE SFP+ v2 zl Module	J9538A			(not supported)	(not supported)	
	20-Port Gig-T / 2-Port SFP+ v2 zl Module	J9548A					
	20-Port Gig-T PoE+ / 2-Port SFP+ v2 zl Module	J9536A					
24p 1GbE SFP v3 zl2 Module	J9988A	KB.15.17 and later	KB.15.17 and later	KB.15.17 and later	KB.15.17 and later	KB.15.17 and later	
12p PoE+ / 12p 1GbE SFP v3 zl2 Module	J9989A						
20p PoE+ / 4p SFP+ v3 zl2 Module	J9990A						
8p 1G/10GbE SFP+ v3 zl2 Module	J9993A						
6108	Switch 6108	J4902A	all software versions	H.07.88 and later	(not supported)	(not supported)	(not supported)
6120	6120G/XG Blade Switch	498358-B21	SX, LX: all versions	SX, LX: all versions	all software versions	all software versions	(not supported)
	6120XG Blade Switch	516733-B21	LH: not supported	LH: not supported			
6200yl	Switch 6200yl 24G mGBIC	J8992A	all software versions	all software versions	all software versions	all software versions	K.13.45 and later
6600	6600 24G Switch	J9263A	K.14.03 and later	K.14.03 and later	(not supported)	(not supported)	K.14.03 and later
	6600 24G 4XG Switch	J9264A					
	6600 48G Switch	J9451A	K.14.24 and later	K.14.24 and later			K.14.24 and later
8100fl	Switch fl 10-Port Mini-GBIC Interface Module	J8735A	all software versions	all software versions	CY.01.02.0050 and later	CY.01.02.0050 and later	(not supported)

## Genuine HPE Mini-GBICs and SFPs (continued)

### Gigabit "B" and "C" versions

HPE Networking Switch Series	Product Name	Product Number	Gigabit-SX, LX, LH (J4858B, J4859B, J4860B)   (J4858C, J4859C, J4860C)		1000BASE-T <sup>1</sup> (J8177B)   (J8177C)		Gigabit-BX (J9142B, J9143B)
			Supported with This Software	Supported with This Software	Supported with This Software	Supported with This Software	Supported with This Software
8200zl	Switch zl 20-Port 10/100/1000 + 4-Port Mini-GBIC Module	J8705A	all software versions	all software versions	all software versions	all software versions	K.13.45 and later
	Switch zl 24-Port Mini-GBIC Module	J8706A					
	20-Port 10/100/1000 PoE+ and 4-Port SFP zl Module	J9308A	K.14.34 and later	K.14.34 and later	K.14.34 and later	K.14.34 and later	K.14.34 and later
	24-Port SFP v2 zl Module	J9537A	K.15.02.0004 and later	K.15.02.0004 and later	K.15.02.0004 and later	K.15.02.0004 and later	K.15.02.0004 and later
	20-Port Gig-T / 4-Port SFP v2 zl Module	J9549A					
	20-Port Gig-T PoE+ / 4-Port SFP v2 zl Module	J9535A					
	12-Port Gig-T PoE+ / 12-Port SFP v2 zl Module	J9637A					
8-Port 10 GbE SFP+ v2 zl Module	J9538A	(not supported)	(not supported)	(not supported)	(not supported)		
20-Port Gig-T / 2-Port SFP+ v2 zl Module	J9548A						
20-Port Gig-T PoE+ / 2-Port SFP+ v2 zl Module	J9536A						
9300m	EP 8-Port Mini-GBIC Redundant Management Module	J4885A	all software versions	all software versions	07.8.00a and later <sup>2</sup>	(not supported)	(not supported)
	EP 16-Port Mini-GBIC Module	J4894A					
9408sl	9400sl 40-Port Mini-GBIC Module	J8684A	all software versions	all software versions	02.1.00c and later	(not supported)	(not supported)

### HPE Networking Legacy Mini-GBIC and SFP Support Information

- HPE Networking products and accessories offer a lifetime warranty, unsurpassed in the marketplace.
- HPE Networking stands behind our products because we build them to precise specifications and thoroughly test them.
- HPE Networking Legacy mini-GBICs and SFPs are specified and tested as rigorously as the devices in which they are used.
- Non-HPE mini-GBICs and SFPs are of unknown quality and therefore cannot be supported with our lifetime warranty.

#### Footnotes

<sup>1</sup> The J8177B/C 1000BASE-T mini-GBIC is not supported in dual-personality ports.

<sup>2</sup> For the 9300m, the J8177B 1000BASE-T mini-GBIC is supported only in EP modules.

<sup>3</sup> 3rd party products from non-HPE vendors are not supported and will not function.

<sup>4</sup> Non-genuine HPE "B version" and "C version" mini-GBICs are not supported and will not function.

<sup>5</sup> Supported: Qualified for operation in HPE switches and warranty support from HPE Networking.

<sup>6</sup> Might function: The HPE switch attempts to enable this non-HPE mini-GBIC.

**Genuine HPE Mini-GBICs and SFPs (continued)**

HPE Networking Switch Series	Product Name	Product Number	Gigabit "A" versions	100-Megabit SFPs		
			Gigabit-SX, LX, LH (J4858A, J4859A, J4860A)	100-FX (J9054B)	100-FX (J9054C: 1990-3613, 1990-4112, 1990-4483)	100-BX (J9099B, J9100B)
			Supported with This Software	Supported with This Software	Supported with This Software	Supported with This Software
1400	Switch 1400 24G	J9078A	all software versions	(not supported)	(not supported)	(not supported)
1410	1410 24G Switch	J9561A	all software versions	all software versions	all software versions	all software versions
1700	Switch 1700 24	J9080A	all software versions	(not supported)	(not supported)	(not supported)
1800	Switch 1800 24G	J9028A/B	all software versions	(not supported)	(not supported)	(not supported)
1810	1810 24G Switch	J9450A	all software versions	all software versions	all software versions	all software versions
	1810 48G Switch	J9660A	(not supported)			(not supported)
	1810 24 v2 Switch 1810 24G v2 Switch PS 1810 24G Switch	J9801A J9803A J9834A	(not supported)	all software versions	all software versions	(not supported)
1820	1820 24G Switch	J9980A	(not supported)	(not supported)	all software versions	(not supported)
	1820 48G Switch	J9981A			(J9054C part number 1990-4483 is not supported in these products.)	
	1820 24G PoE+ (185W) Switch	J9983A				
	1820 48G PoE+ (370W) Switch	J9984A				
2510	Switch 2510 24	J9019A/B	(not supported)	Q.10.04 and later	Q.10.04 and later	Q.11.16 and later
	Switch 2510 48	J9020A		all software versions	all software versions	U.11.10 and later
	Switch 2510G 24	J9279A		all software versions	all software versions	Y.11.03 and later
	Switch 2510G 48	J9280A				
2520	2520 8 PoE Switch	J9137A	(not supported)	all software versions	all software versions	all software versions
	2520 24 PoE Switch	J9138A				
	2520G 8 PoE Switch	J9298A			J.14.32 and later	
	2520G 24 PoE Switch	J9299A				

**Genuine HPE Mini-GBICs and SFPs (continued)**

HPE Networking Switch Series	Product Name	Product Number	Gigabit "A" versions	100-Megabit SFPs					
			Gigabit-SX, LX, LH (J4858A, J4859A, J4860A)	100-FX (J9054B)	100-FX (J9054C: 1990-3613, 1990-4112, 1990-4483)	100-BX (J9099B, J9100B)			
			Supported with This Software	Supported with This Software	Supported with This Software	Supported with This Software			
2530	2530 8 Switch	J9783A	(not supported)	all software versions	all software versions	all software versions			
	2530 24 Switch	J9782A							
	2530 48 Switch	J9781A							
	2530 8G Switch	J9777A							
	2530 24G Switch	J9776A							
	2530 48G Switch	J9775A							
	2530 8 PoE+ Switch	J9780A							
	2530 24 PoE+ Switch	J9779A							
	2530 48 PoE+ Switch	J9778A							
	2530 8G PoE+ Switch	J9774A							
	2530 24G PoE+ Switch	J9773A							
	2530 48G PoE+ Switch	J9772A							
	2530 24G 2SFP+ Switch	J9856A					(not supported)	(not supported)	(not supported)
	2530 48G 2SFP+ Switch	J9855A							
2530 24G PoE+ 2SFP+ Switch	J9854A								
2530 48G PoE+ 2SFP+ Switch	J9853A								
2600	Switch 2626	J4899A/B/C	all software versions	(not supported)	(not supported)	(not supported)			
	Switch 2650	J4900A/B/C							
	Switch 2626 PWR	J8164A							
	Switch 2650 PWR	J8165A							
	Switch 2600 8 PWR	J8762A							
2610	Switch 2610 24	J9085A	(not supported)	all software versions	all software versions	R.11.22 and later			
	Switch 2610 48	J9088A							
	Switch 2610 24 PWR	J9087A							
	Switch 2610 48 PWR	J9089A							
	Switch 2610 24/12PWR	J9086A							
2615	2615 8 PoE Switch	J9565A	(not supported)	all software versions	A.14.07 and later	all software versions			



Genuine HPE Mini-GBICs and SFPs (continued)

HPE Networking Switch Series	Product Name	Product Number	Gigabit "A" versions	100-Megabit SFPs		
			Gigabit-SX, LX, LH (J4858A, J4859A, J4860A)	100-FX (J9054B)	100-FX (J9054C: 1990-3613, 1990-4112, 1990-4483)	100-BX (J9099B, J9100B)
			Supported with This Software	Supported with This Software	Supported with This Software	Supported with This Software
2620	2620 24 Switch 2620 48 Switch 2620 24 PoE+ Switch 2620 48 PoE+ Switch 2620 24 PPOE+ Switch	J9623A J9626A J9625A J9627A J9624A	(not supported)	all software versions	all software versions	all software versions
2800	Switch 2824 Switch 2848	J4903A J4904A	all software versions	i.10.30 and later	1990-3613 and 1990-4112: i.10.30 and later, 1990-4483: not supported	i.10.69 and later
2810	Switch 2810 24G Switch 2810 48G	J9021A J9022A	(not supported)	N.10.07 and later	N.10.07 and later	N.11.14 and later
2900	Switch 2900 24G Switch 2900 48G	J9049A J9050A	(not supported)	T.12.01 and later	T.12.01 and later	T.13.45 and later
2910al	2910al 24G Switch 2910al 48G Switch 2910al 24G PoE+ Switch 2910al 48G PoE+ Switch	J9145A J9147A J9146A J9148A	(not supported)	all software versions	all software versions	all software versions
2915	2915 8G PoE Switch	J9562A	(not supported)	all software versions	A.14.07 and later	all software versions
2920	2920 24G Switch 2920 48G Switch 2920 24G PoE+ Switch 2920 48G PoE+ Switch 2920 48G POE+ 740W Switch 2-Port 10GbE SFP+ Module	J9726A J9728A J9727A J9729A J9836A J9731A	(not supported)	all software versions     (not supported)	all software versions     (not supported)	all software versions     (not supported)

Genuine HPE Mini-GBICs and SFPs (continued)

HPE Networking Switch Series	Product Name	Product Number	Gigabit "A" versions	100-Megabit SFPs		
			Gigabit-SX, LX, LH (J4858A, J4859A, J4860A)	100-FX (J9054B)	100-FX (J9054C: 1990-3613, 1990-4112, 1990-4483)	100-BX (J9099B, J9100B)
			Supported with This Software	Supported with This Software	Supported with This Software	Supported with This Software
Aruba 2930F	2930F 24G 4SFP+ Switch	JL253A	(not supported)	(not supported)	all software versions	all software versions
	2930F 48G 4SFP+ Switch	JL254A				
	2930F 24G PoE+ 4SFP+ Switch	JL255A				
	2930F 48G PoE+ 4SFP+ Switch	JL256A				
	2930F 8G PoE+ 2SFP+ Switch	JL258A				
	2930F 24G PoE+ 4SFP+ TAA Switch	JL263A				
	2930F 48G PoE+ 4SFP+ TAA Switch	JL264A				
	2930F 24G 4SFP Switch	JL259A				
	2930F 48G 4SFP Switch	JL260A				
	2930F 24G PoE+ 4SFP Switch	JL261A				
2930F 48G PoE+ 4SFP Switch	JL262A					
3400cl	Switch 3400cl 24G	J4905A	all software versions	(not supported)	(not supported)	(not supported)
	Switch 3400cl 48G	J4906A				
3500	3500 24 Switch	J9470A	(not supported)	K.14.31 and later	1990-3613: K.14.31 and later, 1990-4112 and 1990-4483: K.15.08.0007 and later	K.14.31 and later
	3500 48 Switch	J9472A				
	3500 24 PoE Switch	J9471A				
	3500 48 PoE Switch	J9473A				
3500yl	Switch 3500yl 24G PWR	J8692A	(not supported)	K.12.01 and later	1990-3613: K.12.01 and later, 1990-4112 and 1990-4483: K.15.08.0007 and later	K.13.45 and later
	Switch 3500yl 48G PWR	J8693A				
	3500yl 24G PoE+ Switch	J9310A		K.14.50 and later	1990-3613: K.14.50 and later, 1990-4112 and 1990-4483: K.15.08.0007 and later	K.14.50 and later
3800	3800 24G 2SFP+ Switch	J9575A	(not supported)	(not supported)	(not supported)	(not supported)
	3800 48G 4SFP+ Switch	J9576A				
	3800 24G PoE+ 2SFP+ Switch	J9573A				
	3800 48G PoE+ 4SFP+ Switch	J9574A				
	3800 24SFP 2SFP+ Switch	J9584A				

Genuine HPE Mini-GBICs and SFPs (continued)

HPE Networking Switch Series	Product Name	Product Number	Gigabit "A" versions Gigabit-SX, LX, LH (J4858A, J4859A, J4860A)	100-FX (J9054B)	100-Megabit SFPs 100-FX (J9054C: 1990-3613, 1990-4112, 1990-4483)		100-BX (J9099B, J9100B)
			Supported with This Software	Supported with This Software	Supported with This Software		Supported with This Software
Aruba 3810M	3810M 24G 1-slot Switch	JL071A*	(not supported)	all software versions	all software versions	all software versions	all software versions
	3810M 48G 1-slot Switch	JL072A*					
	3810M 24G PoE+ 1-slot Switch	JL073A*					
	3810M 48G PoE+ 1-slot Switch	JL074A*					
	3810M 16SFP+ 2-slot Switch	JL075A					
	3810M 40G 8 HPE Smart Rate PoE+ 1-slot Switch	JL076A*					
*For use in the <b>JL075A</b> 3810M switch or in any 3810M switch with a <b>JL083A</b> Aruba 3810M 4SFP+ Module installed.							
4100gl	Switch gl 6-Port Mini-GBIC Module	J4893A	all software versions	(not supported)	(not supported)		(not supported)
	Switch gl 20-Port 10/100/1000 Module	J4908A					
4200vl	Switch vl 4-Port Mini-GBIC Module	J8776A	(not supported)	(not supported)	(not supported)		(not supported)
	Switch vl 20-Port Gig-T + 4-Port SFP Module	J9033A		L.10.24 and later	L.10.24 and later		L.11.16 and later
5300xl	Switch xl 4-Port Mini-GBIC Module	J4878A/B	all software versions	(not supported)	(not supported)		(not supported)
	Switch xl 16-Port 10/100/1000 Module	J4907A					
5400zl	Switch zl 20-Port 10/100/1000 + 4-Port Mini-GBIC Module	J8705A	(not supported)	K.12.01 and later	1990-3613: K.12.01 and later, 1990-4112 and 1990-4483: K.15.08.0007 and later		K.13.45 and later
	Switch zl 24-Port Mini-GBIC Module	J8706A					
	20-Port 10/100/1000 PoE+ and 4-Port SFP zl Module	J9308A	(not supported)	K.14.34 and later	1990-3613: K.14.34 and later, 1990-4112 and 1990-4483: K.15.08.0007 and later		K.14.34 and later
	24-Port SFP v2 zl Module	J9537A	(not supported)	K.15.02.0004 and later	1990-3613: K.15.02.0004 and later, 1990-4112 and 1990-4483: K.15.08.0007 and later		K.15.02.0004 and later
	20-Port Gig-T / 4-Port SFP v2 zl Module	J9549A					
	20-Port Gig-T PoE+ / 4-Port SFP v2 zl Module	J9535A					
12-Port Gig-T PoE+ / 12-Port SFP v2 zl Module	J9637A						
8-Port 10 GbE SFP+ v2 zl Module	J9538A						
20-Port Gig-T / 2-Port SFP+ v2 zl Module	J9548A		(not supported)	(not supported)		(not supported)	
20-Port Gig-T PoE+ / 2-Port SFP+ v2 zl Module	J9536A						

**Genuine HPE Mini-GBICs and SFPs (continued)**

HPE Networking Switch Series	Product Name	Product Number	Gigabit "A" versions Gigabit-SX, LX, LH (J4858A, J4859A, J4860A)	100-FX (J9054B)	100-Megabit SFPs 100-FX (J9054C: 1990-3613, 1990-4112, 1990-4483)	100-BX (J9099B, J9100B)	
			Supported with This Software	Supported with This Software	Supported with This Software	Supported with This Software	
5400R	24-Port SFP v2 zl Module	J9537A	(not supported)	all software versions	all software versions	all software versions	
	20-Port Gig-T / 4-Port SFP v2 zl Module	J9549A					
	20-Port Gig-T PoE+ / 4-Port SFP v2 zl Module	J9535A					
	12-Port Gig-T PoE+ / 12-Port SFP v2 zl Module	J9637A		(not supported)	(not supported)	(not supported)	
	8-Port 10 GbE SFP+ v2 zl Module	J9538A					
	20-Port Gig-T / 2-Port SFP+ v2 zl Module	J9548A					
20-Port Gig-T PoE+ / 2-Port SFP+ v2 zl Module	J9536A	(not supported)	KB.15.17 and later	KB.15.17 and later	KB.15.17 and later		
24p 1GbE SFP v3 zl2 Module	J9988A						
12p PoE+ / 12p1GbE SFP v3 zl2 Module	J9989A						
8p 1G/10GbE SFP+ v3 zl2 Module	J9993A						
20p PoE+ /4p SFP+ v3 zl2 Module	J9990A						
6108	Switch 6108	J4902A	all software versions	(not supported)	(not supported)	(not supported)	
6120	6120G/XG Blade Switch 6120XG Blade Switch	498358-B21 516733-B21	(not supported)	(not supported)	(not supported)	(not supported)	
6200yl	Switch 6200yl-24G-mGBIC	J8992A	(not supported)	K.12.01 and later	1990-3613: K.12.01 and later, 1990-4112 and 1990-4483: K.15.08.0007 and later	K.13.45 and later	
6600	6600 24G Switch	J9263A	(not supported)	K.14.03 and later	1990-3613: K.14.03 and later, 1990-4112 and 1990-4483: K.15.08.0007 and later	K.14.03 and later	
	6600 24G 4XG Switch	J9264A					
	6600 48G Switch	J9451A		K.14.24 and later	1990-3613: K.14.24 and later, 1990-4112 and 1990-4483: K.15.08.0007 and later	K.14.24 and later	
8100fl	Switch fl 10-Port Mini-GBIC Interface Module	J8735A	(not supported)	(not supported)	(not supported)	(not supported)	
8200zl	Switch zl 20-Port 10/100/1000 + 4-Port Mini-GBIC Module	J8705A	(not supported)	all software versions	1990-3613: all software versions, 1990-4112 and 1990-4483: K.15.08.0007 and later	K.13.45 and later	
	Switch zl 24-Port Mini-GBIC Module	J8706A					
	20-Port 10/100/1000 PoE+ and 4-Port SFP zl Module	J9308A		K.14.34 and later	1990-3613: K.14.34 and later, 1990-4112 and 1990-4483: K.15.08.0007 and later	K.14.34 and later	
	24-Port SFP v2 zl Module	J9537A		(not supported)	K.15.02.0004 and later	1990-3613: K.15.02.0004 and later, 1990-4112 and 1990-4483: K.15.08.0007 and later	K.15.02.0004 and later
	20-Port Gig-T / 4-Port SFP v2 zl Module	J9549A					
20-Port Gig-T PoE+ / 4-Port SFP v2 zl Module	J9535A						
12-Port Gig-T PoE+ / 12-Port SFP v2 zl Module	J9637A						
8-Port 10 GbE SFP+ v2 zl Module	J9538A	(not supported)	(not supported)	(not supported)	(not supported)		
20-Port Gig-T / 2-Port SFP+ v2 zl Module	J9548A						
20-Port Gig-T PoE+ / 2-Port SFP+ v2 zl Module	J9536A						

**Genuine HPE Mini-GBICs and SFPs (continued)**

HPE Networking Switch Series	Product Name	Product Number	Gigabit "A" versions Gigabit-SX, LX, LH (J4858A, J4859A, J4860A)	100-FX (J9054B)	100-Megabit SFPs 100-FX (J9054C: 1990-3613, 1990-4112, 1990-4483)	100-BX (J9099B, J9100B)
			Supported with This Software	Supported with This Software	Supported with This Software	Supported with This Software
9300m	EP 8-Port Mini-GBIC Redundant Management Module EP 16-Port Mini-GBIC Module	J4885A J4894A	all software versions	(not supported)	(not supported)	(not supported)
9408sl	9400sl 40-Port Mini-GBIC Module	J8684A	all software versions	(not supported)	(not supported)	(not supported)

© Copyright 2014 - 2016 Hewlett Packard Enterprise Development LP  
 The information contained herein is subject to change without notice.  
 5200-1980  
 May 2016

